



Aalborg Universitet

AALBORG UNIVERSITY
DENMARK

Incremental Refinement using a Gaussian Test Channel and MSE Distortion

Østergaard, Jan; Zamir, Ram

Published in:
Information Theory and Applications (ITA)

Publication date:
2012

Document Version
Early version, also known as pre-print

[Link to publication from Aalborg University](#)

Citation for published version (APA):
Østergaard, J., & Zamir, R. (2012). Incremental Refinement using a Gaussian Test Channel and MSE Distortion. In *Information Theory and Applications (ITA)*

General rights

Copyright and moral rights for the publications made accessible in the public portal are retained by the authors and/or other copyright owners and it is a condition of accessing publications that users recognise and abide by the legal requirements associated with these rights.

- Users may download and print one copy of any publication from the public portal for the purpose of private study or research.
- You may not further distribute the material or use it for any profit-making activity or commercial gain
- You may freely distribute the URL identifying the publication in the public portal -

Take down policy

If you believe that this document breaches copyright please contact us at vbn@aub.aau.dk providing details, and we will remove access to the work immediately and investigate your claim.

Incremental source coding using a Gaussian test channel and MSE distortion

Jan Østergaard

Department of Electronic Systems
Aalborg University, Denmark
janoe@ieee.org

Ram Zamir

Department of Electrical Engineering-Systems
Tel Aviv University, Israel
zamir@eng.tau.ac.il

Abstract—The additive rate-distortion function (ARDF) is defined as the minimum mutual information over an additive test channel followed by estimation. We consider the special case of quadratic distortion and where the noise in the test channel is Gaussian distributed and show that unconditional incremental refinement, i.e., where each refinement is encoded independently of the other refinements, is ARDF optimal in the limit of low resolution, independently of the source distribution.

I. INTRODUCTION

The additive rate-distortion function (ARDF) consists of an additive test channel followed by estimation. We are interested in analyzing the ARDF at low resolutions and consider the special case where the test channel's noise is Gaussian and the distortion measure is the MSE. We establish a link to the mutual information – minimum mean squared estimation (I-MMSE) relation of Guo et al. [8] and show that unconditional incremental refinement, i.e., where each refinement is encoded independently of the other refinements, is ARDF optimal in the limit of low resolution, independently of the source distribution.

II. RESULTS

We refer the reader to [1] for the proofs of the lemmas presented in this section.

Lemma 1. Let $Y_i = \sqrt{\gamma}X + N_i, i = 0, \dots, k-1$, where $N_i \perp\!\!\!\perp X, \forall i$. Moreover, let X be arbitrarily distributed with variance σ_X^2 and let N_0, \dots, N_{k-1} , be zero-mean unit-variance i.i.d. Gaussian distributed. Then

$$\begin{aligned} \lim_{\gamma \rightarrow 0} \frac{1}{\gamma} I(X; Y_0, \dots, Y_{k-1}) &= k \lim_{\gamma \rightarrow 0} \frac{1}{\gamma} I(X; \sqrt{\gamma}X + N_0) \\ &= \frac{k \log_2(e)}{2} \sigma_X^2 \end{aligned}$$

and

$$\lim_{\gamma \rightarrow 0} \frac{1}{\gamma} \left[\frac{1}{\text{var}(X|Y_1, \dots, Y_{k-1})} - \frac{1}{\sigma_X^2} \right] = k,$$

where $\text{var}(X|Y)$ denotes the MMSE due to estimating X from Y .

Lemma 2. Let $Y_i = \sqrt{\gamma}X + N_i, i = 0, \dots, k-1$, where $N_i \perp\!\!\!\perp X, \forall i$, and N_0, \dots, N_{k-1} . Let X be arbitrarily distributed with variance σ_X^2 and let N_0, \dots, N_{k-1} , be zero-mean unit-variance i.i.d. Gaussian distributed. Let Z be arbitrarily distributed and correlated with X but independent of

$N_i, \forall i$. Then

$$\lim_{\gamma \rightarrow 0} \frac{1}{\gamma} I(X; Y_0, \dots, Y_{k-1}|Z) = \frac{k \log_2(e)}{2} \text{var}(X|Z).$$

Remark 1. Lemmas 1 and 2 basically extend the I-MMSE relation of Guo et al. [2] to the case of several variables and side information, respectively. By doing this, an interesting connection to source coding is made. In particular, let an arbitrarily distributed source X be encoded into k representations $Y_i = \sqrt{\gamma}X + N_i$ where $\{N_i\}, i = 1, \dots, k$, are mutually independent, Gaussian distributed, and independent of X . Then Lemma 1 reveals that $I(X; Y_1, \dots, Y_k) \approx \sum_i I(X; Y_i)$ at low rates. This is interesting since conditional source coding is generally more complicated than unconditional source coding, i.e., creating descriptions that are individually optimal and at the same time jointly optimal is a long standing problem in information theory, where it is known as the multiple descriptions problem [3]. Furthermore, if side information Z , where Z is independent of $N_i, i = 1, \dots, k$, but arbitrarily jointly distributed with X , is available both at the encoder and decoder, then Lemma 2 shows that $I(X; Y_1, \dots, Y_k|Z) \approx \sum_i I(X; Y_i|Z)$.

REFERENCES

- [1] J. Østergaard and R. Zamir, "Incremental refinement using a Gaussian test channel," in *IEEE Int. Symposium on Information Theory (ISIT)*, August 2011, pp. 2233 – 2237.
- [2] D. Guo, S. Shamai, and S. Verdú, "Mutual information and minimum mean-square error in Gaussian channels," *IEEE Trans. Inform. Theory*, vol. 51, pp. 1261 – 1282, April 2005.
- [3] A. A. E. Gamal and T. M. Cover, "Achievable rates for multiple descriptions," *IEEE Trans. Inform. Theory*, vol. IT-28, no. 6, pp. 851 – 857, Nov. 1982.